



39.95 EUR

incl. 19% VAT, plus [shipping](#)

- Intel Rapid BIOS Boot
- DDR-II RAM
- 1.33Ghz CPU
- 3 years warranty

Support:  [Manual \[EN\]](#) | [Heatsink-Height](#)

The Intel® Desktop Board D201GLY is an innovative solution for the sub-value market segment. With an Intel® Celeron® processor and graphics integrated on the board, this board enables easy system integration and helps you to achieve a lower system cost. This board has 10/100 LAN and can support up to six Hi-Speed USB 2.0 ports, providing both connectivity and ease of use for your computing needs such as email and Internet access, instant messaging and Voice Over IP (VoIP).

The Intel Desktop Board D201GLY is built in smaller uATX-Compatible form factor providing lower power consumption and low sound emission.

| | |
|------------------------|--|
| Form Factor | uATX (6.75 inches by 6.75 inches [171.45 millimeters by 171.45 millimeters]) (ITX compatible) |
| Processor | Integrated Intel® Celeron® 215 processor (1.33 GHz) with a 533 MHz system bus |
| Memory | One 240-pin DDR2 SDRAM Dual Inline Memory Module (DIMM) sockets Support for DDR2 533 MHz and DDR2 400 MHz DIMMs Support for up to 1 GB of system memory |
| Chipset | SiS* SiS662 |
| Audio | ADI* AD1888 audio codec |
| Video | Integrated SiS Mirage* 1 graphic engine |
| I/O Control | Winbond* W83627DHG-B based Legacy I/O controller for hardware management, serial, parallel, and PS/2* ports |
| LAN Support | 10/100 Mb/s/sec LAN subsystem using the Broadcom* LAN adapter device |
| Peripheral Interfaces | Six USB 2.0 ports One parallel ATA IDE interface with UDMA 33, ATA-66/100/133 support One S-Video output port (optional) One serial port One parallel port PS/2* keyboard and mouse ports |
| Expansion Capabilities | One PCI Conventional* bus connector |

Note : The CPU heatsink has a height of 40mm. That's why it does not fit into every enclosure.

Compatible with :

- Voom
- Voom-2
- M300(-LCD)
- Travla C137

Not compatible with :

- M200(-LCD)
- Morex enclosures

PicoPSU & M3-ATX : You can only directly stick in the standard picoPSU-120 power supply. Other picoPSU models and M3-ATX can only be connected with an additional ATX extension cable.

For Operating you need a P4 adapter or a PSU with P4 connector